

AFX LED FIXTURE MATRIX

| Fixture | Suffix | Nominal Power | Suffix | Beam Type/Angle | Suffix | Driver | Suffix | LED Colour | Suffix | Trim Finish | Suffix |
|--|--------|-------------------------|--------|-----------------|--------|-----------------------------|--------|------------|--------|--------------------------------|----------------|
| Multigiro | MG | 5.3w, 8.6w, 6.8w, 10.3w | | All | | 700ma, 1050ma, 350ma, 525ma | | All | | White Matt Silver Chrome | WH MS CH |
| Multiquadro | MQ | As above | | All | | As above | | All | | As above | |
| For Multiple Mutigiro and Multiquadro fixtures please insert 2x, 3x, 4x etc. to the catalogue reference ie. MG.4x.L2.0025..... | | | | | | | | | | | |
| Mic Hal | MH | 5.3w, 8.6w | | All | | 700ma, 1050ma | | All | | Matt Silver | MS |
| For Multiple Mic Hal fixtures please insert 2x, 3x, 4x etc. to the catalogue reference ie. MH.4x.L2.0025..... | | | | | | | | | | | |
| Maxigiro | MG | 23w, 32w, 29w, 41w | | | | 1050ma, 1400ma | | | | White Matt Silver Chrome | WH MS CH |
| Shutter | SH | 5.3w, 8.6w, 6.8w, 10.3w | | All | | 700ma, 1050ma, 350ma, 525ma | | All | | Matt Silver | |
| Bullet | BU | 5.3w, 8.6w, 6.8w, 10.3w | | All | | 700ma, 1050ma, 350ma, 525ma | | All | | Black Matt Silver | BL MS |
| Robust | RO | 23w, 32w, 29w, 41w | | All | | 1050ma, 1400ma | | All | | As above | |
| Miro | MI | As above | | All | | As Above | | All | | Matt Silver | MS |
| Uran | UR | All | | All | | As above | | All | | Stainless Steel | SS |
| | | | | | | | | | | | |
| Power | | | | | | | | | | | |
| LED1 | L1 | 5.3w | L1 | All | | 700ma | | WW, CW | | | |
| LED2 | L2 | 8.6w | L2 | All | | 1050ma | | WW, CW | | | |
| LED3 | L3 | 6.8w | L3 | All | | 350ma | | RGB | | | |
| LED4 | L4 | 10.3w | L4 | All | | 525ma | | RGB | | | |
| LED5 | L5 | 23w | L5 | All | | 1050ma | | WW, CW | | | |
| LED6 | L6 | 32w | L6 | All | | 1400ma | | WW, CW | | | |
| LED7 | L7 | 29w | L7 | All | | 1050ma | | RGB | | | |
| LED8 | L8 | 41w | L8 | All | | 1400ma | | RGB | | | |
| | | | | | | | | | | | |
| Beam Type/Angle | | | | | | | | | | | |
| 10 | 0010 | All | | Conical | 0010 | | | All | | | |
| 25 | 0025 | All | | Conical | 0025 | | | All | | | |
| 40 | 0040 | All | | Conical | 0040 | | | All | | | |
| 15/40 | 1540 | All | | Line Beam | 1540 | | | All | | | |
| | | | | | | | | | | | |
| Driver | | | | | | | | | | | |
| Standard | STD | All | | | | Standard | STD | All | | | |
| DMX | DMX | All | | | | DMX | DMX | All | | | |
| DALI | DLI | All | | | | DALI | DLI | All | | | |
| | | | | | | | | | | | |
| LED Colour | | | | | | | | | | | |
| Warm White | WW | 5.3w, 8.6w, 23w, 32w | | | | | | Warm White | WW | | |
| Cool White | CW | 5.3w, 8.6w, 23w, 32w | | | | | | Cool White | CW | | |
| RGB | RGB | 6.8w, 10.3w, 29w, 41w | | | | | | RGB | RGB | | |
| EXAMPLE: Multigiro fixture with 5.3w LED, 25 degree beam angle, standard on/off driver, Warm White LED with White Bezel - Catalogue reference: MG.L1.0025.STD.WW.WH | | | | | | | | | | | |